

About this course

This is a free self-study course outline written by Saving Planets. It is not a university course, it carries no academic credit, and no school is involved.

Its scope follows the second semester of calculus-based college physics (electricity and magnetism, with a first look at optics). It is modeled on the topics and depth of MIT OpenCourseWare 8.02, Caltech's Ph1b and Ph1c, Georgia Tech PHYS 2212 and the free OpenStax University Physics Volume 2, which we link throughout. None of those authors or schools endorses this page.

What we add: every unit ties to real clean-energy or Earth-observation work with a cited public source (generators, solar panels, electric cars, the power grid, Earth's magnetic field, space weather, satellite sensors), every number on the page is re-computed by a checking script before it goes live, and every lab has a free PhET version plus a safe low-voltage home version.

Work through it in order. Each unit has goals, key ideas, equations, step-by-step examples, practice with full answers, common mistakes, flashcards and a quiz. Your progress is saved only in this browser.

How this course helps save the planet

Almost all clean electricity is electromagnetism at work. Wind and hydro turbines spin generators that run on Faraday's law, solar panels push charge with built-in electric fields, electric cars turn current into motion with magnetic forces, and the grid uses transformers and high voltage to move power with small losses.

Electromagnetic waves are also how we watch the planet: satellites such as Landsat 9 and GOES-19 read visible, infrared and microwave light to map crops, forests, water and storms. And Earth's own magnetic field shields us, while space weather from the Sun can push currents into power lines. Each unit ends with a short, sourced section. Values that are not from a source are labeled as sample values.

Before you start

Prerequisites

- Physics I: forces, energy, momentum, circular motion and oscillations.
- Calculus I and II: derivatives, integrals, and exponential growth and decay.
- Vectors: components, dot and cross products (taught briefly where needed).

- Calculus III helps with Gauss's and Ampère's laws in integral form but is not required.

How to study

- Draw the field or the circuit first. Most E&M mistakes are sign or direction mistakes.
- Solve with symbols first, then put in numbers in SI units, and check the units of the answer.
- Use symmetry: before applying Gauss's or Ampère's law, ask which way the field must point and on what it can depend.
- Do every practice problem on paper before opening the answer.
- Predict, then test it in the PhET simulation. A wrong prediction you fix sticks better than a right guess.
- Retake the quizzes a few days later. Spaced practice beats one long session.

Lab equipment (for the wet labs)

- A computer or tablet for the free PhET simulations (they run in a browser).
- A digital multimeter and a few AA batteries with a battery holder (low voltage only).
- A small set of resistors (100 Ω to 10 k Ω), a 100 μ F or larger electrolytic capacitor rated above the battery voltage, jumper wires or a breadboard.
- A smartphone with a magnetometer app (most phones have the sensor), a small compass, a few fridge magnets.
- A clear glass or plastic box of water, a laser pointer of class 2 or lower or a narrow flashlight beam, a protractor.
- Spreadsheet software for graphs and fits.

Suggested 15-week schedule

About 6 to 9 hours a week: reading, practice problems and, in lab weeks, the lab.

Week	Unit	Topics	Reading
1	Charge, Coulomb's Law and Electric Fields	Charge, Coulomb's law, superposition	OpenStax UP2 5.1–5.3
2	Charge, Coulomb's Law and Electric Fields	Electric fields, continuous charge, field lines; Lab A	UP2 5.4–5.6
3	Gauss's Law	Flux and Gauss's law; conductors	UP2 6.1–6.4
4	Electric Potential and Capacitance	Potential energy, potential, equipotentials	UP2 7.1–7.5
5	Electric Potential and Capacitance	Capacitance, energy, dielectrics; Lab B	UP2 8.1–8.4
6	Current, Resistance and DC Circuits	Current, resistance, power	UP2 9.1–9.5

Week	Unit	Topics	Reading
7	Current, Resistance and DC Circuits	DC circuits, Kirchhoff's rules, RC circuits; Lab C	UP2 10.1–10.5
8	Magnetic Fields and Forces	Magnetic force, particle orbits, motors; midterm practice	UP2 11.1–11.5
9	Sources of Magnetic Fields: Biot–Savart and Ampère	Biot–Savart, Ampère's law, solenoids; Lab D	UP2 12.1–12.7
10	Electromagnetic Induction: Faraday and Lenz	Faraday's and Lenz's laws, generators; Lab E	UP2 13.1–13.7
11	Inductance, RL and LC Circuits	Inductance, RL and LC circuits	UP2 14.1–14.6
12	AC Circuits, Transformers and the Power Grid	AC circuits, resonance, power, transformers	UP2 15.1–15.6
13	Maxwell's Equations, Electromagnetic Waves and Optics	Maxwell's equations, EM waves, energy and the spectrum	UP2 16.1–16.5
14	Maxwell's Equations, Electromagnetic Waves and Optics	Optics: reflection, refraction, polarization, lenses; Lab F	UP3 1.1–1.7, 2.4
15	Review	Review and final practice set	All units

Your progress

Tick units and labs as you finish them, and take the quizzes. Progress and quiz scores are saved only in this browser, never sent to us.

Charge, Coulomb's Law and Electric Fields

Electric charge, conductors and insulators, Coulomb's law, the electric field of point charges and continuous charge, field lines, and charges moving in fields.

Learning objectives

By the end of this unit you can:

- Use Coulomb's law with vectors and superposition.
- Find the electric field of point charges and simple charge distributions.
- Sketch field lines and read them.
- Find the force and acceleration of a charge in a field.

Key concepts

- Charge comes in two signs, is conserved, and is quantized in units of $e = 1.602 \times 10^{-19} \text{ C}$.
- Coulomb's law: $F = k|q_1q_2|/r^2$, along the line between the charges; like charges repel.
- The electric field $E = F/q$ is the force per unit charge. A point charge makes $E = kq/r^2$, pointing away from positive charge.
- Fields add as vectors (superposition). For continuous charge, add up $dE = k dq/r^2$ with an integral.
- A charge in a field feels $F = qE$, so an electron accelerates opposite to E .

Key equations

$$F = k \frac{|q_1 q_2|}{r^2}, \quad k = \frac{1}{4\pi\epsilon_0}$$

Coulomb's law

$$\vec{E} = \frac{\vec{F}}{q}, \quad E = \frac{k|q|}{r^2}$$

Electric field of a point charge

$$\vec{E} = \int \frac{k dq}{r^2} \hat{r}$$

Continuous charge

$$\vec{F} = q\vec{E}$$

Force on a charge

Worked examples, step by step

Example 1.1 Charges of $+3.0 \mu\text{C}$ and $-5.0 \mu\text{C}$ sit 0.20 m apart. Find the force between them.

1. $F = k|q_1q_2|/r^2 = 8.988 \times 10^9 \times (3.0 \times 10^{-6})(5.0 \times 10^{-6})/0.20^2$.
2. Opposite signs attract.

Answer: 3.37 N , attractive.

Example 1.2 Find the field 0.30 m from a 2.0 nC point charge.

1. $E = kq/r^2 = 8.988 \times 10^9 \times 2.0 \times 10^{-9}/0.09$.

Answer: $\approx 200 \text{ N/C}$, pointing away from the charge.

Example 1.3 Charges of $+4.0 \text{ nC}$ and -4.0 nC are 0.10 m apart. Find the field at the midpoint.

1. Each charge is 0.05 m away and gives $E = kq/r^2 = 14,380 \text{ N/C}$.
2. Both fields point toward the negative charge, so they add.

Answer: $28,760 \text{ N/C}$ ($2.88 \times 10^4 \text{ N/C}$) toward the negative charge.

Practice problems

Work each on paper first, then check.

1. Find the electric force between the proton and electron in hydrogen ($r = 5.29 \times 10^{-11} \text{ m}$).

$$F = ke^2/r^2 \approx 8.24 \times 10^{-8} \text{ N}.$$

2. How many times stronger is the electric repulsion of two protons than their gravitational attraction?

$$ke^2/(Gm_p^2) \approx 1.23 \times 10^{36}, \text{ independent of distance.}$$

3. An electron sits in a 200 N/C field. Find the force and acceleration.

$$F = eE = 3.20 \times 10^{-17} \text{ N}; a = F/m_e \approx 3.52 \times 10^{13} \text{ m/s}^2, \text{ opposite to } E.$$

4. Where is the field zero between $+q$ and $+4q$ a distance d apart?

$$kq/x^2 = 4kq/(d-x)^2 \text{ gives } x = d/3 \text{ from } +q.$$

Common misconceptions

Myth: A bigger charge feels a bigger force from a smaller one.

Actually: Newton's third law: the forces are equal and opposite.

Myth: Field lines are paths charges follow.

Actually: They show force direction; a moving charge can leave a curved line.

Myth: The field is zero wherever there is no charge.

Actually: Empty space can hold a strong field; only the charge density is zero there.

Flashcards

Elementary charge

$$e = 1.602 \times 10^{-19} \text{ C.}$$

Coulomb's law

$$F = k|q_1q_2|/r^2.$$

Electric field

$$E = F/q.$$

Point-charge field

$$E = kq/r^2.$$

Superposition

Fields from several charges add as vectors.

Field lines

Start on + charge, end on – charge; denser means stronger.

Self-check quiz

1. Doubling the distance between two charges changes the force by... _____

×2

× $\frac{1}{2}$

× $\frac{1}{4}$

×4

× $\frac{1}{4}$. Inverse square.

2. The field of a positive point charge points...

toward it

away from it

in circles

nowhere

away from it. Direction of force on a positive test charge.

3. An electron in a field pointing east accelerates...

east

west

north

not at all

west. $F = qE$ with $q < 0$.

4. The SI unit of electric field is...

N/C

C/N

J

T

N/C. Force per charge (also V/m).

Try this quiz again

How this helps save the planet

A solar cell works because sunlight frees charges that a built-in electric field then pushes apart. The U.S. Department of Energy explains that sunlight absorbed in a PV cell creates electrical charges

that move in response to an internal electric field, so electricity flows. Every solar panel is a sheet of carefully engineered electric fields.

On Saving Planets: [Physics I](#)

Sources: [U.S. DOE: How does solar work?](https://www.energy.gov/eere/solar/how-does-solar-work) (<https://www.energy.gov/eere/solar/how-does-solar-work>) · [OpenStax UP2, 5.3 Coulomb's law](#) (<https://openstax.org/books/university-physics-volume-2/pages/5-3-coulombs-law>)

Free learning resources

- [OpenStax UP2, 5.3 Coulomb's law](https://openstax.org/books/university-physics-volume-2/pages/5-3-coulombs-law) (<https://openstax.org/books/university-physics-volume-2/pages/5-3-coulombs-law>): Free textbook section.
- [OpenStax UP2, 5.4 Electric field](https://openstax.org/books/university-physics-volume-2/pages/5-4-electric-field) (<https://openstax.org/books/university-physics-volume-2/pages/5-4-electric-field>): Fields and superposition.
- [OpenStax UP2, 5.5 Fields of charge distributions](https://openstax.org/books/university-physics-volume-2/pages/5-5-calculating-electric-fields-of-charge-distributions) (<https://openstax.org/books/university-physics-volume-2/pages/5-5-calculating-electric-fields-of-charge-distributions>): Integrals for E.
- [PhET: Coulomb's Law](https://phet.colorado.edu/en/simulations/coulombs-law) (<https://phet.colorado.edu/en/simulations/coulombs-law>): Interactive.



I finished this unit

Gauss's Law

Electric flux, Gauss's law, and using symmetry to find fields of spheres, lines and sheets; conductors in electrostatic equilibrium.

Learning objectives

By the end of this unit you can:

- Compute electric flux through a surface.
- State Gauss's law and choose a Gaussian surface that matches the symmetry.
- Find fields of spherical, cylindrical and planar charge.
- Explain why the field inside a conductor is zero and charge sits on its surface.

Key concepts

- Flux $\Phi = \oint \mathbf{E} \cdot d\mathbf{A}$ counts field lines through a surface.
- Gauss's law: the net flux out of any closed surface equals the enclosed charge divided by ϵ_0 .
- Gauss's law is always true but only useful when symmetry makes E constant on the surface: spheres, long lines, large sheets.
- Outside a uniform sphere of charge, the field is the same as a point charge at the center.
- In a conductor in equilibrium $E = 0$ inside, excess charge sits on the surface, and E just outside is perpendicular to the surface.

Key equations

$$\Phi_E = \oint \mathbf{E} \cdot d\mathbf{A} = \frac{Q_{\text{enc}}}{\epsilon_0}$$

Gauss's law

$$E = \frac{\lambda}{2\pi\epsilon_0 r}$$

Long line of charge

$$E = \frac{\sigma}{2\epsilon_0}$$

Large sheet of charge

$$E = \frac{\sigma}{\epsilon_0}$$

Worked examples, step by step

Example 2.1 A closed surface surrounds a 1.0 nC charge. Find the net flux.

1. $\Phi = Q/\epsilon_0 = 1.0 \times 10^{-9}/8.854 \times 10^{-12}$; the shape does not matter.

Answer: $\approx 113 \text{ N}\cdot\text{m}^2/\text{C}$.

Example 2.2 A long wire carries 2.0 nC per meter. Find E at 0.10 m.

1. Use a cylinder: $E(2\pi rL) = \lambda L/\epsilon_0$, so $E = \lambda/(2\pi\epsilon_0 r) = 2k\lambda/r$.
2. $E = 2 \times 8.988 \times 10^9 \times 2.0 \times 10^{-9}/0.10$.

Answer: $\approx 360 \text{ N/C}$, pointing radially outward.

Example 2.3 A large sheet holds $\sigma = 5.0 \text{ }\mu\text{C}/\text{m}^2$. Find E near it.

1. A pillbox through the sheet: $2EA = \sigma A/\epsilon_0$.

Answer: $E = \sigma/(2\epsilon_0) \approx 2.82 \times 10^5 \text{ N/C}$, the same at every distance near the sheet.

Practice problems

Work each on paper first, then check.

1. A 1.0 μC charge sits on a 0.10 m metal sphere. Find E at 0.50 m from the center and at 0.05 m.

Outside: $kQ/r^2 = 3.60 \times 10^4 \text{ N/C}$. Inside the conductor: 0.

2. Why does a car protect you from lightning?

Charge stays on the outer metal surface, so the field inside is small (a Faraday cage).

3. A cube surrounds a dipole. What is the net flux?

Zero: the enclosed charge is zero.

4. How does E from a line of charge fall with distance?

As $1/r$, slower than a point charge's $1/r^2$.

Common misconceptions

Myth: Zero flux means zero field everywhere on the surface.

Actually: Only the total is zero; field can go in on one side and out on another.

Myth: Gauss's law only works for symmetric charges.

Actually: It always holds; symmetry is what makes it easy to use.

Myth: Charges outside the surface change the flux.

Actually: They change E on the surface but add zero net flux.

Flashcards

Electric flux

$$\Phi = \oint \mathbf{E} \cdot d\mathbf{A}.$$

Gauss's law

$$\Phi = Q_{\text{enc}}/\epsilon_0.$$

Line of charge

$$E = \lambda/(2\pi\epsilon_0 r).$$

Sheet of charge

$$E = \sigma/(2\epsilon_0).$$

Conductor

$E = 0$ inside; charge on the surface.

Faraday cage

A closed conductor shields its inside.

Self-check quiz

1. Net flux through a closed surface depends on...

its shape

the enclosed charge

its area

outside charges

the enclosed charge. $Q_{\text{enc}}/\epsilon_0$.

2. Inside a conductor in equilibrium, E is...

maximum

zero

kQ/r^2

σ/ϵ_0

zero. Free charges rearrange until $E = 0$.

3. E near a large charged sheet varies with distance as...

$1/r^2$

$1/r$

constant

r

constant. $\sigma/(2\epsilon_0)$.

4. The best Gaussian surface for a long wire is a...

sphere

cube

coaxial cylinder

flat disk

coaxial cylinder. Matches the symmetry.

Try this quiz again

How this helps save the planet

Gauss's law has a magnetic twin: the net magnetic flux through any closed surface is zero, because there are no magnetic monopoles. Earth's field is a good example. NOAA's National Centers for

Environmental Information say more than 90% of the field measured at the surface is generated in Earth's outer core. Every field line that leaves the planet comes back to it.

On Saving Planets: [Space Weather](#)

Sources: NOAA NCEI: Geomagnetism frequently asked questions (<https://www.ngdc.noaa.gov/geomag/faqgeom.shtml>)

· [OpenStax UP2, 6.3 Applying Gauss's law](https://openstax.org/books/university-physics-volume-2/pages/6-3-applying-gausss-law) (<https://openstax.org/books/university-physics-volume-2/pages/6-3-applying-gausss-law>)

Free learning resources

- [OpenStax UP2, 6.2 Explaining Gauss's law](https://openstax.org/books/university-physics-volume-2/pages/6-2-explaining-gausss-law) (<https://openstax.org/books/university-physics-volume-2/pages/6-2-explaining-gausss-law>): Flux and the law.
- [OpenStax UP2, 6.3 Applying Gauss's law](https://openstax.org/books/university-physics-volume-2/pages/6-3-applying-gausss-law) (<https://openstax.org/books/university-physics-volume-2/pages/6-3-applying-gausss-law>): Spheres, lines, sheets.
- [OpenStax UP2, 6.4 Conductors in equilibrium](https://openstax.org/books/university-physics-volume-2/pages/6-4-conductors-in-electrostatic-equilibrium) (<https://openstax.org/books/university-physics-volume-2/pages/6-4-conductors-in-electrostatic-equilibrium>): Conductors.
- [MIT OpenCourseWare 8.02 Physics II: Electricity and Magnetism](https://ocw.mit.edu/courses/8-02-physics-ii-electricity-and-magnetism-spring-2019/) (<https://ocw.mit.edu/courses/8-02-physics-ii-electricity-and-magnetism-spring-2019/>): Lectures and problem sets.



I finished this unit

Electric Potential and Capacitance

Potential energy and potential, equipotentials, finding E from V , capacitors in series and parallel, stored energy, and dielectrics.

Learning objectives

By the end of this unit you can:

- Compute potential and potential energy of point charges.
- Relate E and V : $E = -dV/dx$.
- Find capacitance and combine capacitors.
- Compute stored energy and the effect of a dielectric.

Key concepts

- Potential V is potential energy per charge (volts = joules per coulomb). Only differences matter.
- A point charge gives $V = kq/r$; potentials add as numbers, not vectors.
- The field points downhill in potential: $E = -dV/dx$. Equipotentials are perpendicular to field lines.
- A capacitor stores charge $Q = CV$. A parallel-plate capacitor has $C = \epsilon_0 A/d$.
- Stored energy $U = \frac{1}{2}CV^2$. A dielectric with constant κ multiplies C by κ .
- Parallel capacitors add; in series, reciprocals add.

Key equations

$$V = \frac{kq}{r}, \quad \Delta U = q \Delta V$$

Potential of a point charge

$$E_x = -\frac{dV}{dx}$$

Field from potential

$$C = \frac{Q}{V} = \frac{\kappa \epsilon_0 A}{d}$$

Parallel-plate capacitor

$$U = \frac{1}{2}CV^2$$

Stored energy

$$C_{\parallel} = C_1 + C_2, \quad \frac{1}{C_s} = \frac{1}{C_1} + \frac{1}{C_2}$$

Combinations

Worked examples, step by step

Example 3.1 Find the potential 0.30 m from a 2.0 nC charge.

$$1. V = kq/r = 8.988 \times 10^9 \times 2.0 \times 10^{-9}/0.30.$$

Answer: ≈ 59.9 V.

Example 3.2 An electron starts from rest and moves through a 100 V potential difference. Find its speed.

$$1. e\Delta V = \frac{1}{2}mv^2.$$

$$2. v = \sqrt{(2 \times 1.602 \times 10^{-19} \times 100/9.109 \times 10^{-31})}.$$

Answer: $\approx 5.93 \times 10^6$ m/s.

Example 3.3 Plates of 0.010 m² sit 1.0 mm apart and connect to 12 V. Find C, Q and U.

$$1. C = \epsilon_0 A/d = 8.854 \times 10^{-12} \times 0.010/0.001 = 88.5 \text{ pF}.$$

$$2. Q = CV = 1.06 \text{ nC}.$$

$$3. U = \frac{1}{2}CV^2 = 6.37 \text{ nJ}.$$

Answer: 88.5 pF, 1.06 nC, 6.37 nJ.

Practice problems

Work each on paper first, then check.

1. Combine 2 μF and 3 μF in series and in parallel.

Series 1.2 μF ; parallel 5 μF .

2. Fill the 88.5 pF capacitor with a dielectric of $\kappa = 3.4$.

C = 301 pF.

3. A large supercapacitor of 3,000 F is charged to 2.7 V (sample values). How much energy does it hold?

$U = \frac{1}{2}CV^2 \approx 10.9 \text{ kJ}$, a tiny fraction of an EV battery but delivered in seconds.

4. $V = 4x^2$ volts. Find E at $x = 2 \text{ m}$.

$E = -dV/dx = -16 \text{ V/m}$ (pointing toward $-x$).

Common misconceptions

Myth: Potential and potential energy are the same thing.

Actually: $U = qV$; V is per unit charge.

Myth: High voltage alone is what makes a shock dangerous.

Actually: Current through the body matters; voltage drives it through the body's resistance.

Myth: Where $V = 0$, $E = 0$.

Actually: Midway between $+q$ and $-q$, $V = 0$ but E is large.

Flashcards

Electric potential

$V = U/q$, in volts.

Point-charge potential

$V = kq/r$.

Field from potential

$E = -dV/dx$.

Capacitance

$C = Q/V$; farads.

Parallel plates

$C = \kappa\epsilon_0 A/d$.

Capacitor energy

$U = \frac{1}{2}CV^2$.

Electron volt

$1 \text{ eV} = 1.602 \times 10^{-19} \text{ J}$.

Self-check quiz

1. 1 volt equals...

1 J/C

1 C/J

1 N/C

1 W/A²

1 J/C. Energy per charge.

2. Halving the plate gap of a capacitor makes C...

half

double

four times

unchanged

double. $C = \epsilon_0 A/d$.

3. Doubling the voltage on a capacitor multiplies stored energy by...

2

4

$\frac{1}{2}$

1

4. $U \propto V^2$.

4. Equipotential lines meet field lines at...

0°

45°

90°

any angle

90°. No work along an equipotential.

Try this quiz again

How this helps save the planet

Electric cars store energy in batteries, not capacitors, because a capacitor holds far less energy per kilogram. The supercapacitor in the practice set holds about 10.9 kJ, about 3.04 watt-hours. Capacitors earn their place where power must flow in or out in seconds, such as smoothing the output of power electronics in EVs, solar inverters and wind turbines.

On Saving Planets: [Physics I](#)

Sources: [FuelEconomy.gov \(DOE/EPA\): All-electric vehicles](#) (<https://www.fueleconomy.gov/feg/evtech.shtml>) · [OpenStax UP2, 8.3 Energy stored in a capacitor](#) (<https://openstax.org/books/university-physics-volume-2/pages/8-3-energy-stored-in-a-capacitor>)

Free learning resources

- [OpenStax UP2, 7.2 Electric potential and potential difference](#) (<https://openstax.org/books/university-physics-volume-2/pages/7-2-electric-potential-and-potential-difference>): Potential.
- [OpenStax UP2, 7.3 Calculations of electric potential](#) (<https://openstax.org/books/university-physics-volume-2/pages/7-3-calculations-of-electric-potential>): Potential of charge distributions.
- [OpenStax UP2, 8.1 Capacitors and capacitance](#) (<https://openstax.org/books/university-physics-volume-2/pages/8-1-capacitors-and-capacitance>): Capacitors.
- [OpenStax UP2, 8.4 Capacitor with a dielectric](#) (<https://openstax.org/books/university-physics-volume-2/pages/8-4-capacitor-with-a-dielectric>): Dielectrics.
- [PhET: Capacitor Lab: Basics](#) (<https://phet.colorado.edu/en/simulations/capacitor-lab-basics>): Interactive.



I finished this unit

Current, Resistance and DC Circuits

Current and drift speed, resistivity and Ohm's law, power, EMF and internal resistance, series and parallel resistors, Kirchhoff's rules, and RC circuits.

Learning objectives

By the end of this unit you can:

- Relate current to drift speed and resistance to resistivity.
- Use Ohm's law and $P = IV$.
- Reduce series-parallel networks and apply Kirchhoff's rules.
- Analyze charging and discharging RC circuits.

Key concepts

- Current $I = dQ/dt$; in a wire $I = nqv_dA$, and the drift speed is tiny even though signals travel near light speed.
- Resistance $R = \rho L/A$. Ohm's law $V = IR$ holds for ohmic materials.
- Power $P = IV = I^2R = V^2/R$.
- Series resistors add; in parallel, reciprocals add.
- Kirchhoff: currents into a junction sum to zero; voltage changes around any loop sum to zero.
- An RC circuit charges as $V = V_0(1 - e^{-(t/RC)})$; the time constant is $\tau = RC$.

Key equations

$$I = \frac{dQ}{dt} = nqv_dA$$

Current and drift speed

$$R = \rho \frac{L}{A}, \quad V = IR$$

Resistance and Ohm's law

$$P = IV = I^2R$$

Electrical power

$$\sum I = 0, \quad \sum \Delta V = 0$$

Kirchhoff's rules

$$V_C = V_0 \left(1 - e^{-t/RC}\right)$$

Charging capacitor

Worked examples, step by step

Example 4.1 Find the resistance of 100 m of copper wire 1.0 mm in diameter ($\rho = 1.68 \times 10^{-8} \Omega \cdot \text{m}$).

1. $A = \pi(0.5 \times 10^{-3})^2 = 7.85 \times 10^{-7} \text{ m}^2$.
2. $R = \rho L/A = 1.68 \times 10^{-8} \times 100/7.85 \times 10^{-7}$.

Answer: $\approx 2.14 \Omega$.

Example 4.2 Two batteries (12 V and 6 V) and three resistors: loop 1 has 12 V, $R_1 = 2 \Omega$ and the shared $R_3 = 6 \Omega$; loop 2 has 6 V, $R_2 = 3 \Omega$ and R_3 . Find the currents.

1. Junction: $I_3 = I_1 + I_2$.
2. Loop 1: $12 = 2I_1 + 6I_3$. Loop 2: $6 = 3I_2 + 6I_3$.
3. Solve: $I_1 = 2 \text{ A}$, $I_2 = -0.667 \text{ A}$, $I_3 = 1.33 \text{ A}$.

Answer: $I_1 = 2 \text{ A}$; $I_2 = -0.667 \text{ A}$ (the minus sign means the 12 V battery is pushing current backward through the 6 V one, charging it); $I_3 = 1.33 \text{ A}$.

Example 4.3 A $100 \mu\text{F}$ capacitor charges from a 9 V battery through $10 \text{ k}\Omega$. Find τ and the voltage after 1 s and 3 s.

1. $\tau = RC = 10^4 \times 10^{-4} = 1.0 \text{ s}$.
2. $V(1) = 9(1 - e^{-1})$; $V(3) = 9(1 - e^{-3})$.

Answer: 1.0 s; 5.69 V; 8.55 V.

Practice problems

Work each on paper first, then check.

1. A 60 W bulb runs on 120 V. Find its current and resistance.

$$I = 0.5 \text{ A}; R = 240 \Omega.$$

2. Find the equivalent of $6\ \Omega$ and $3\ \Omega$ in parallel, then the current from 12 V through that pair in series with $4\ \Omega$.

$$2\ \Omega; I = 12/6 = 2\ \text{A}.$$

3. Find the drift speed for 1 A in the 1.0 mm copper wire ($n = 8.5 \times 10^{28}\ \text{m}^{-3}$).

$$v_d = I/(neA) \approx 9.4 \times 10^{-5}\ \text{m/s}, \text{ about a third of a meter per hour.}$$

4. A solar panel has 60 cells in series, each giving 0.6 V (sample values). What is the panel voltage?
How do you double the current instead?

36 V; put two panels in parallel.

Common misconceptions

Myth: Current is used up in a resistor.

Actually: Charge is conserved; energy is converted, not current.

Myth: Electrons race through wires at near light speed.

Actually: The signal does; the electrons drift at fractions of a millimeter per second.

Myth: A battery supplies constant current.

Actually: It supplies roughly constant EMF; the current depends on the circuit.

Flashcards

Current

$$I = dQ/dt; \text{ amperes.}$$

Ohm's law

$$V = IR.$$

Resistivity

$$R = \rho L/A.$$

Power

$$P = IV = I^2 R = V^2/R.$$

Junction rule

$$\Sigma I = 0.$$

Loop rule

$$\Sigma \Delta V = 0.$$

RC time constant

$$\tau = RC.$$

Self-check quiz

1. Doubling a wire's length doubles its... _____

resistivity

resistance

current

area

resistance. $R = \rho L/A$.

2. Two equal resistors R in parallel give... _____

$2R$

R

$R/2$

R^2

$R/2$. $1/R + 1/R$.

3. After one time constant a charging capacitor is at... _____

37%

50%

63%

100%

63%. $1 - e^{(-1)}$.

4. Kirchhoff's loop rule comes from conservation of... _____

charge

energy

momentum

mass

energy. Potential is energy per charge.

Try this quiz again

How this helps save the planet

A solar panel is a DC circuit. Cells are wired in series to raise the voltage and panels in parallel to raise the current, exactly as in the practice set. A cell pushes charge one way only, so a panel's output is direct current; it must be converted to alternating current before it can join the grid (Unit 9). The U.S. Department of Energy explains how the cells themselves work.

On Saving Planets: [Earth Observation](#)

Sources: [U.S. DOE: How does solar work?](https://www.energy.gov/eere/solar/how-does-solar-work) (<https://www.energy.gov/eere/solar/how-does-solar-work>) · [OpenStax UP2, 10.3 Kirchhoff's rules](#) (<https://openstax.org/books/university-physics-volume-2/pages/10-3-kirchhoffs-rules>)

Free learning resources

- [OpenStax UP2, 9.1 Electrical current](https://openstax.org/books/university-physics-volume-2/pages/9-1-electrical-current) (<https://openstax.org/books/university-physics-volume-2/pages/9-1-electrical-current>): Current.
- [OpenStax UP2, 9.3 Resistivity and resistance](https://openstax.org/books/university-physics-volume-2/pages/9-3-resistivity-and-resistance) (<https://openstax.org/books/university-physics-volume-2/pages/9-3-resistivity-and-resistance>): Resistance.
- [OpenStax UP2, 10.2 Resistors in series and parallel](https://openstax.org/books/university-physics-volume-2/pages/10-2-resistors-in-series-and-parallel) (<https://openstax.org/books/university-physics-volume-2/pages/10-2-resistors-in-series-and-parallel>): Combinations.
- [OpenStax UP2, 10.5 RC circuits](https://openstax.org/books/university-physics-volume-2/pages/10-5-rc-circuits) (<https://openstax.org/books/university-physics-volume-2/pages/10-5-rc-circuits>): RC circuits.
- [PhET: Ohm's Law](https://phet.colorado.edu/en/simulations/ohms-law) (<https://phet.colorado.edu/en/simulations/ohms-law>): Interactive.



I finished this unit

Magnetic Fields and Forces

The magnetic force on moving charges and currents, circular motion of charged particles, torque on a current loop, and how electric motors work.

Learning objectives

By the end of this unit you can:

- Use $F = q\mathbf{v} \times \mathbf{B}$ with the right-hand rule.
- Find the radius and frequency of a charged particle's circular orbit.
- Find the force on a current-carrying wire and the torque on a loop.
- Explain how a DC motor turns current into rotation.

Key concepts

- A magnetic field pushes on moving charge: $F = q\mathbf{v} \times \mathbf{B}$, perpendicular to both $\mathbf{v}$ and $\mathbf{B}$. It does no work, so it changes direction, not speed.
- A charge moving across a uniform field circles with radius $r = mv/(|q|B)$ and cyclotron frequency $f = |q|B/(2\pi m)$, independent of speed.
- A wire carrying current I in field $\mathbf{B}$ feels $F = I\mathbf{L} \times \mathbf{B}$.
- A current loop has magnetic moment $\mu = NIA$ and feels torque $\tau = \mu B \sin \theta$. That torque is what spins an electric motor.
- Crossed $\mathbf{E}$ and $\mathbf{B}$ fields pass only particles with $\mathbf{v} = \mathbf{E}/\mathbf{B}$ (a velocity selector).

Key equations

$$\mathbf{F} = q\mathbf{v} \times \mathbf{B}$$

Magnetic force on a charge

$$r = \frac{mv}{|q|B}, \quad f = \frac{|q|B}{2\pi m}$$

Circular motion in a field

$$\mathbf{F} = I\mathbf{L} \times \mathbf{B}$$

Force on a current

$$\tau = NIAB \sin \theta$$

Torque on a loop

Worked examples, step by step

Example 5.1 A solar-wind proton moves at 400 km/s perpendicular to a 50 μT field (sample values). Find the radius of its circle.

$$1. r = mv/(eB) = 1.673 \times 10^{-27} \times 4 \times 10^5 / (1.602 \times 10^{-19} \times 5 \times 10^{-5}).$$

Answer: ≈ 83.5 m. Charged particles spiral tightly along field lines instead of crossing them.

Example 5.2 A 0.20 m wire carrying 200 A sits perpendicular to a 0.50 T field. Find the force.

$$1. F = ILB = 200 \times 0.20 \times 0.50.$$

Answer: 20 N.

Example 5.3 A motor coil has 100 turns of area 0.01 m^2 carrying 2 A in a 0.5 T field. Find the maximum torque.

$$1. \tau = NIAB = 100 \times 2 \times 0.01 \times 0.5.$$

Answer: 1.0 N·m, when the coil's plane is parallel to the field.

Practice problems

Work each on paper first, then check.

1. Find the cyclotron frequency of a proton in a 1 T field.

$$f = eB/(2\pi m_p) \approx 15.2 \text{ MHz.}$$

2. An electron moves at 1×10^5 m/s across a 50 μT field. Find r .

$$r = m_e v / (eB) \approx 1.14 \text{ cm.}$$

3. What speed passes undeflected through $E = 10^4$ V/m and $B = 0.1$ T?

$$v = E/B = 10^5 \text{ m/s.}$$

4. Can a static magnetic field speed up a charge?

No: $F \perp v$, so it does no work.

Common misconceptions

Myth: Magnetic force points along the field.

Actually: It is perpendicular to B and to v .

Myth: A charge at rest feels a magnetic force.

Actually: Only moving charges do.

Myth: Bigger speed means a higher cyclotron frequency.

Actually: The radius grows with speed, but the frequency does not.

Flashcards

Lorentz force

$$F = q(E + v \times B).$$

Right-hand rule

Fingers v , curl to B , thumb F for positive q .

Cyclotron radius

$$r = mv/(qB).$$

Force on a wire

$$F = ILB \sin \theta.$$

Magnetic moment

$$\mu = NIA.$$

Motor torque

$$\tau = NIAB \sin \theta.$$

Self-check quiz

1. The magnetic force on a charge moving parallel to B is... _____

maximum

zero

qvB

qE

zero. $\sin 0 = 0$.

2. The SI unit of magnetic field is the... _____

gauss

tesla

weber

henry

tesla. $1 \text{ T} = 1 \text{ N}/(\text{A}\cdot\text{m})$; $1 \text{ G} = 10^{-4} \text{ T}$.

3. Doubling a charged particle's speed in a uniform B changes its radius by...

$\times 1/2$

$\times 1$

$\times 2$

$\times 4$

$\times 2$. $r = mv/(qB)$.

4. The torque on a motor coil is largest when its plane is...

perpendicular to B

parallel to B

at 30°

any angle

parallel to B. μ is then perpendicular to B.

Try this quiz again

How this helps save the planet

Electric cars run on magnetic torque: current in the motor's coils sits in a magnetic field, and $\tau = NIAB \sin \theta$ turns the wheels. FuelEconomy.gov says EVs convert over 77% of the electrical energy from the grid to power at the wheels, while gasoline cars convert only about 12% to 30% of the energy in their fuel.

Earth's field, between about 25 and 65 μT at the surface according to NOAA, bends incoming charged particles of the solar wind into tight spirals, as in the first worked example. Particles trapped this way are guided along field lines toward the poles, where they light up the aurora.

On Saving Planets: [Space Weather](#)

Sources: [FuelEconomy.gov \(DOE/EPA\): All-electric vehicles \(https://www.fueleconomy.gov/feg/evtech.shtml\)](#) · [NOAA NCEI: Geomagnetism frequently asked questions \(https://www.ngdc.noaa.gov/geomag/faqgeom.shtml\)](#)

Free learning resources

- [OpenStax UP2, 11.3 Motion of a charged particle in a magnetic field \(https://openstax.org/books/university-physics-volume-2/pages/11-3-motion-of-a-charged-particle-in-a-magnetic-field\)](https://openstax.org/books/university-physics-volume-2/pages/11-3-motion-of-a-charged-particle-in-a-magnetic-field): Circular motion.
- [OpenStax UP2, 11.4 Magnetic force on a current-carrying conductor \(https://openstax.org/books/university-physics-volume-2/pages/11-4-magnetic-force-on-a-current-carrying-conductor\)](https://openstax.org/books/university-physics-volume-2/pages/11-4-magnetic-force-on-a-current-carrying-conductor): Force on wires.
- [OpenStax UP2, 11.5 Force and torque on a current loop \(https://openstax.org/books/university-physics-volume-2/pages/11-5-force-and-torque-on-a-current-loop\)](https://openstax.org/books/university-physics-volume-2/pages/11-5-force-and-torque-on-a-current-loop): Motors.
- [PhET: Magnets and Electromagnets \(https://phet.colorado.edu/en/simulations/magnets-and-electromagnets\)](https://phet.colorado.edu/en/simulations/magnets-and-electromagnets): Interactive.



I finished this unit

Sources of Magnetic Fields: Biot–Savart and Ampère

How currents make magnetic fields: the Biot–Savart law, fields of wires, loops and solenoids, forces between parallel currents, and Ampère’s law.

Learning objectives

By the end of this unit you can:

- Use the Biot–Savart law for a wire and a loop.
- Apply Ampère’s law to wires and solenoids.
- Find the force between parallel currents.
- Compare man-made fields with Earth’s field.

Key concepts

- Biot–Savart: each bit of current $I d\mathbf{l}$ makes $d\mathbf{B} = (\mu_0/4\pi) I d\mathbf{l} \times \hat{\mathbf{r}}/r^2$. Field lines circle the current (right-hand rule: thumb along I , fingers curl with $\mathbf{B}$).
- A long straight wire: $B = \mu_0 I/(2\pi r)$. At the center of a loop of radius R : $B = \mu_0 I/(2R)$.
- Ampère’s law: $\oint \mathbf{B} \cdot d\mathbf{l} = \mu_0 I_{\text{enc}}$. Like Gauss’s law, it is easiest with symmetry.
- Inside a long solenoid $B = \mu_0 nI$, uniform, where n is turns per meter.
- Parallel currents attract; opposite currents repel, with force per length $\mu_0 I_1 I_2/(2\pi d)$.

Key equations

$$d\mathbf{B} = \frac{\mu_0}{4\pi} \frac{I d\mathbf{l} \times \hat{\mathbf{r}}}{r^2}$$

Biot–Savart law

$$B = \frac{\mu_0 I}{2\pi r}$$

Long straight wire

$$\oint \mathbf{B} \cdot d\mathbf{l} = \mu_0 I_{\text{enc}}$$

Ampère’s law

$$B = \mu_0 nI$$

Long solenoid

$$\frac{F}{L} = \frac{\mu_0 I_1 I_2}{2\pi d}$$

Parallel wires

Worked examples, step by step

Example 6.1 A transmission line carries 1,000 A (sample value). Find B at 20 m and compare it with Earth's field.

$$1. B = \mu_0 I / (2\pi r) = 4\pi \times 10^{-7} \times 1,000 / (2\pi \times 20).$$

Answer: 10 μ T, smaller than Earth's 25–65 μ T surface field.

Example 6.2 A solenoid has 1,000 turns per meter and carries 2 A. Find B inside.

$$1. B = \mu_0 n I = 4\pi \times 10^{-7} \times 1,000 \times 2.$$

Answer: $\approx$ 2.51 mT, about 50 times Earth's field.

Example 6.3 Two parallel wires 1 cm apart each carry 10 A in the same direction. Find the force per meter.

$$1. F/L = \mu_0 I_1 I_2 / (2\pi d) = 4\pi \times 10^{-7} \times 100 / (2\pi \times 0.01).$$

Answer: 2.0 mN/m, attractive.

Practice problems

Work each on paper first, then check.

1. Find B at the center of a 5 cm radius loop carrying 5 A.

$$B = \mu_0 I / (2R) \approx 62.8 \mu\text{T}.$$

2. A wire carries 2 A. Find B at 1, 2 and 4 cm.

40, 20 and 10 μ T: halving with each doubling of distance.

3. Use Ampère's law to find B inside a thick wire of radius a at $r < a$ (uniform current).

$$B(2\pi r) = \mu_0 I r^2 / a^2, \text{ so } B = \mu_0 I r / (2\pi a^2), \text{ growing linearly from the center.}$$

4. What is B outside an ideal toroid?

Zero: the loop encloses no net current.

Common misconceptions

Myth: Magnetic field lines start and end on poles.

Actually: They form closed loops; there are no monopoles.

Myth: Ampère's law gives B for any current.

Actually: It always holds, but it gives B directly only with symmetry.

Myth: The field of a wire points along the wire.

Actually: It circles the wire.

Flashcards

Biot-Savart

$$dB = (\mu_0/4\pi) I \, dl \times \hat{r}/r^2.$$

Wire field

$$B = \mu_0 I / (2\pi r).$$

Loop center

$$B = \mu_0 I / (2R).$$

Ampère's law

$$\oint \mathbf{B} \cdot d\mathbf{l} = \mu_0 I_{\text{enc}}.$$

Solenoid

$$B = \mu_0 n I.$$

Parallel currents

Same direction attract.

Self-check quiz

1. B from a long wire falls with distance as...

$1/r^2$

$1/r$

constant

r

$1/r \cdot \mu_0 I / (2\pi r)$.

2. Inside a long solenoid, B depends on...

radius

turns per meter and current

length only

distance from the axis

turns per meter and current. $B = \mu_0 nI$.

3. Two wires with currents in opposite directions...

attract

repel

feel no force

twist

repel. Opposite currents repel.

4. μ_0 is about...

8.85×10^{-12}

1.26×10^{-6}

9×10^9

3×10^8

1.26×10^{-6} , $4\pi \times 10^{-7} \text{ T}\cdot\text{m/A}$.

[Try this quiz again](#)

How this helps save the planet

Earth's own field is made by currents: NOAA explains that more than 90% of it is generated in the outer core by what NOAA calls Earth's internal dynamo: moving, electrically conducting material that carries current. The Biot–Savart law is the bridge between those currents and the field a compass reads. NOAA's World Magnetic Model describes this main field.

On Saving Planets: [Space Weather](#)

Sources: NOAA NCEI: Geomagnetism frequently asked questions (<https://www.ngdc.noaa.gov/geomag/faqgeom.shtml>)
· OpenStax UP2, 12.1 The Biot–Savart law (<https://openstax.org/books/university-physics-volume-2/pages/12-1-the-biot-savart-law>)

Free learning resources

- OpenStax UP2, 12.1 The Biot–Savart law (<https://openstax.org/books/university-physics-volume-2/pages/12-1-the-biot-savart-law>): Biot–Savart.
- OpenStax UP2, 12.5 Ampère's law (<https://openstax.org/books/university-physics-volume-2/pages/12-5-amperes-law>): Ampère's law.
- PhET: Magnet and Compass (<https://phet.colorado.edu/en/simulations/magnet-and-compass>): Interactive.
- MIT OpenCourseWare 8.02 Physics II: Electricity and Magnetism (<https://ocw.mit.edu/courses/8-02-physics-ii-electricity-and-magnetism-spring-2019/>): Lectures and problem sets.



I finished this unit

Electromagnetic Induction: Faraday and Lenz

Magnetic flux, Faraday's law, Lenz's law, motional EMF, induced electric fields, eddy currents, and the generators behind wind and hydro power.

Learning objectives

By the end of this unit you can:

- Compute magnetic flux and the EMF from a changing flux.
- Use Lenz's law to find the direction of induced current.
- Find motional EMF for a moving rod.
- Compute the output of an AC generator and the power of a hydro plant.

Key concepts

- Magnetic flux $\Phi_B = \int \mathbf{B} \cdot d\mathbf{A}$, in webers.
- Faraday's law: a changing flux through a coil of N turns induces EMF $\varepsilon = -N d\Phi_B/dt$.
- Lenz's law (the minus sign): the induced current opposes the change in flux that caused it, which is energy conservation.
- A rod of length L moving at v across B has motional EMF $\varepsilon = BLv$.
- A coil spinning at angular speed ω in B gives $\varepsilon = NBA\omega \sin \omega t$: alternating current. Turning it takes mechanical work, which is how generators convert motion into electrical energy.

Key equations

$$\Phi_B = \int \mathbf{B} \cdot d\mathbf{A}$$

Magnetic flux

$$\varepsilon = -N \frac{d\Phi_B}{dt}$$

Faraday's law

$$\varepsilon = BLv$$

Motional EMF

$$\varepsilon(t) = NBA\omega \sin \omega t$$

AC generator

$$P = \eta \rho g Q h$$

Hydropower

Worked examples, step by step

Example 7.1 A generator coil has 100 turns of area 0.04 m^2 spinning at 60 rev/s in a 0.5 T field. Find the peak EMF.

1. $\omega = 2\pi \times 60 = 377 \text{ rad/s}$.
2. $\varepsilon_{\text{max}} = NBA\omega = 100 \times 0.5 \times 0.04 \times 377$.

Answer: $\approx 754 \text{ V}$.

Example 7.2 A 200-turn coil of area 0.01 m^2 sees B rise from 0 to 0.3 T in 0.5 s. Find the average EMF.

1. $\Delta\Phi = BA = 0.003 \text{ Wb}$ per turn.
2. $\varepsilon = N\Delta\Phi/\Delta t = 200 \times 0.003/0.5$.

Answer: 1.2 V.

Example 7.3 A hydro plant passes $100 \text{ m}^3/\text{s}$ through a 50 m head at 90% efficiency (sample values). Find its power.

1. $P = \eta \rho g Q h = 0.9 \times 1,000 \times 9.81 \times 100 \times 50$.

Answer: $\approx 44.1 \text{ MW}$.

Practice problems

Work each on paper first, then check.

1. A 0.2 m rod moves at 3 m/s across a 0.5 T field. Find the EMF.

$$BLv = 0.3 \text{ V}.$$

2. A magnet's north pole approaches a loop. Which way does the induced current flow, seen from the magnet?

Counterclockwise, making a north face that repels the approaching magnet.

3. Why is it harder to turn a generator when lamps are switched on?

The current in the coil feels a magnetic torque opposing the motion (Lenz); that is where the electrical energy comes from.

4. Doubling a generator's spin rate changes its peak EMF by...?

×2: $\varepsilon_{\text{max}} = NBA\omega$.

Common misconceptions

Myth: A strong but steady field induces current.

Actually: Only a changing flux induces EMF.

Myth: Lenz's law opposes the field.

Actually: It opposes the change in flux.

Myth: Generators make energy.

Actually: They convert mechanical work into electrical energy.

Flashcards

Magnetic flux

$\Phi = BA \cos \theta$; webers.

Faraday's law

$\varepsilon = -N d\Phi/dt$.

Lenz's law

Induced current opposes the change.

Motional EMF

$\varepsilon = BLv$.

Generator

$\varepsilon = NBA\omega \sin \omega t$.

Eddy currents

Induced loops in bulk metal; used in braking.

Self-check quiz

1. Faraday's law relates EMF to...

flux

rate of change of flux

current

resistance

rate of change of flux. $\varepsilon = -N \, d\Phi/dt$.

2. The minus sign in Faraday's law is...

Ohm's law

Lenz's law

Gauss's law

a convention only

Lenz's law. Opposes the change.

3. A coil spinning in a steady field produces...

DC

AC

no EMF

static charge

AC. $\varepsilon \propto \sin \omega t$.

4. The SI unit of magnetic flux is the...

tesla

weber

henry

farad

weber. $1 \, \text{Wb} = 1 \, \text{T} \cdot \text{m}^2$.

Try this quiz again

How this helps save the planet

Wind and hydro power are Faraday's law. The U.S. Department of Energy explains that wind turns a turbine's blades around a rotor, which spins a generator that creates electricity, and that hydropower plants use turbines and generators to convert the kinetic energy of flowing water into electricity for the grid.

On Saving Planets: [Physics I](#)

Sources: [U.S. DOE: How do wind turbines work?](https://www.energy.gov/eere/wind/how-do-wind-turbines-work) (<https://www.energy.gov/eere/wind/how-do-wind-turbines-work>) · [U.S. DOE: How hydropower works](https://www.energy.gov/eere/water/how-hydropower-works) (<https://www.energy.gov/eere/water/how-hydropower-works>)

Free learning resources

- [OpenStax UP2, 13.1 Faraday's law](https://openstax.org/books/university-physics-volume-2/pages/13-1-faradays-law) (<https://openstax.org/books/university-physics-volume-2/pages/13-1-faradays-law>): Faraday.
- [OpenStax UP2, 13.2 Lenz's law](https://openstax.org/books/university-physics-volume-2/pages/13-2-lenzs-law) (<https://openstax.org/books/university-physics-volume-2/pages/13-2-lenzs-law>): Lenz.
- [OpenStax UP2, 13.3 Motional EMF](https://openstax.org/books/university-physics-volume-2/pages/13-3-motional-emf) (<https://openstax.org/books/university-physics-volume-2/pages/13-3-motional-emf>): Moving conductors.
- [OpenStax UP2, 13.6 Electric generators and back EMF](https://openstax.org/books/university-physics-volume-2/pages/13-6-electric-generators-and-back-emf) (<https://openstax.org/books/university-physics-volume-2/pages/13-6-electric-generators-and-back-emf>): Generators.
- [PhET: Faraday's Law](https://phet.colorado.edu/en/simulations/faradays-law) (<https://phet.colorado.edu/en/simulations/faradays-law>): Interactive.



I finished this unit

Inductance, RL and LC Circuits

Mutual and self-inductance, energy stored in magnetic fields, RL circuits and their time constant, and LC oscillations.

Learning objectives

By the end of this unit you can:

- Find the self-inductance of a solenoid and the EMF of an inductor.
- Analyze current growth and decay in RL circuits.
- Compute energy in an inductor and magnetic energy density.
- Find the frequency of an LC oscillator.

Key concepts

- A changing current in one coil induces EMF in another: $\varepsilon_2 = -M \, dI_1/dt$ (mutual inductance).
- A coil opposes changes in its own current: $\varepsilon = -L \, dI/dt$. A long solenoid has $L = \mu_0 N^2 A/l$.
- In an RL circuit the current rises as $I = (\varepsilon/R)(1 - e^{-(t/\tau)})$ with $\tau = L/R$.
- An inductor stores $U = \frac{1}{2}LI^2$; any magnetic field stores energy density $u = B^2/(2\mu_0)$.
- An LC circuit swaps energy between capacitor and inductor at $\omega = 1/\sqrt{LC}$, the electrical twin of a mass on a spring.

Key equations

$$\varepsilon = -L \frac{dI}{dt}, \quad L = \frac{\mu_0 N^2 A}{l}$$

Self-inductance

$$I = \frac{\varepsilon}{R} \left(1 - e^{-t/\tau} \right), \quad \tau = \frac{L}{R}$$

RL circuit

$$U = \frac{1}{2}LI^2, \quad u_B = \frac{B^2}{2\mu_0}$$

Magnetic energy

$$\omega = \frac{1}{\sqrt{LC}}$$

Worked examples, step by step

Example 8.1 A solenoid has 500 turns, cross-section $1.0 \times 10^{-3} \text{ m}^2$ and length 0.25 m. Find L , then τ with a 10Ω resistor.

$$1. L = \mu_0 N^2 A / l = 4\pi \times 10^{-7} \times 250,000 \times 10^{-3} / 0.25 = 1.26 \text{ mH}.$$

$$2. \tau = L/R = 0.126 \text{ ms}.$$

Answer: 1.26 mH; 0.126 ms.

Example 8.2 How much energy does that inductor store at 2 A?

$$1. U = \frac{1}{2} L I^2 = \frac{1}{2} \times 1.257 \times 10^{-3} \times 4.$$

Answer: $\approx 2.51 \text{ mJ}$.

Example 8.3 Find the oscillation frequency of a 10 mH inductor with a $1 \mu\text{F}$ capacitor.

$$1. f = 1/(2\pi\sqrt{LC}) = 1/(2\pi\sqrt{(10^{-8})}).$$

Answer: $\approx 1.59 \text{ kHz}$.

Practice problems

Work each on paper first, then check.

1. Two coils have $M = 0.01 \text{ H}$. The current in one changes at 100 A/s . Find the EMF in the other.

1 V.

2. What fraction of its final current does an RL circuit reach after 1τ and 3τ ?

63% and 95%.

3. Find the magnetic energy density of Earth's $50 \mu\text{T}$ field.

$$B^2/(2\mu_0) \approx 9.9 \times 10^{-4} \text{ J/m}^3.$$

4. Why can switching off an inductive load make a spark?

Stopping I quickly makes $L \, dI/dt$ huge.

Common misconceptions

Myth: An inductor resists current.

Actually: It resists changes in current; with steady DC it is just a wire.

Myth: Inductors store energy in charge.

Actually: In the magnetic field.

Myth: LC oscillations last forever.

Actually: Real resistance damps them (an RLC circuit, Unit 9).

Flashcards

Self-inductance

$$\varepsilon = -L \, di/dt.$$

Mutual inductance

$$\varepsilon_2 = -M \, di_1/dt.$$

Solenoid inductance

$$L = \mu_0 N^2 A/l.$$

RL time constant

$$\tau = L/R.$$

Inductor energy

$$U = \frac{1}{2}LI^2.$$

LC frequency

$$\omega = 1/\sqrt{LC}.$$

Self-check quiz

1. The SI unit of inductance is the...

farad

henry

tesla

ohm

henry. $1 \, \text{H} = 1 \, \text{V}\cdot\text{s}/\text{A}.$

2. Doubling the turns of a solenoid multiplies L by...

2

4

$\frac{1}{2}$

1

4. $L \propto N^2$.

3. The RL time constant is...

RL

L/R

R/L

$\sqrt{LC}$

L/R . $\tau = L/R$.

4. An LC circuit is the electrical analog of...

friction

a mass on a spring

a falling body

a lever

a mass on a spring. Energy swaps back and forth.

Try this quiz again

How this helps save the planet

Space weather is induction on a planetary scale. NOAA's Space Weather Prediction Center explains that geomagnetic storms create harmful geomagnetically induced currents in the power grid and

pipelines, as well as beautiful aurora. The storms are driven by coronal mass ejections, which NOAA says leave the Sun at speeds from below 250 km/s to nearly 3,000 km/s; the fastest Earth-directed ones arrive in as little as 15 to 18 hours.

On Saving Planets: [Space Weather](#) · [Solar Orbiter](#)

Sources: NOAA Space Weather Prediction Center: Geomagnetic storms (<https://www.swpc.noaa.gov/phenomena/geomagnetic-storms>) · NOAA Space Weather Prediction Center: Coronal mass ejections (<https://www.swpc.noaa.gov/phenomena/coronal-mass-ejections>)

Free learning resources

- [OpenStax UP2, 14.1 Mutual inductance](https://openstax.org/books/university-physics-volume-2/pages/14-1-mutual-inductance) (<https://openstax.org/books/university-physics-volume-2/pages/14-1-mutual-inductance>): Mutual inductance.
- [OpenStax UP2, 14.2 Self-inductance and inductors](https://openstax.org/books/university-physics-volume-2/pages/14-2-self-inductance-and-inductors) (<https://openstax.org/books/university-physics-volume-2/pages/14-2-self-inductance-and-inductors>): Inductors.
- [OpenStax UP2, 14.4 RL circuits](https://openstax.org/books/university-physics-volume-2/pages/14-4-rl-circuits) (<https://openstax.org/books/university-physics-volume-2/pages/14-4-rl-circuits>): RL circuits.
- [OpenStax UP2, 14.5 Oscillations in an LC circuit](https://openstax.org/books/university-physics-volume-2/pages/14-5-oscillations-in-an-lc-circuit) (<https://openstax.org/books/university-physics-volume-2/pages/14-5-oscillations-in-an-lc-circuit>): LC circuits.



I finished this unit

AC Circuits, Transformers and the Power Grid

Alternating current, RMS values, reactance and impedance, phasors, RLC resonance, power factor, transformers, and why the grid transmits at high voltage.

Learning objectives

By the end of this unit you can:

- Convert between peak and RMS values.
- Find reactance, impedance, phase and current in a series RLC circuit.
- Compute average power and power factor.
- Use transformer ratios and explain high-voltage transmission.

Key concepts

- Household AC is sinusoidal; meters read RMS values, with $V_{\text{rms}} = V_0/\sqrt{2}$.
- Inductors have reactance $X_L = \omega L$ and capacitors $X_C = 1/(\omega C)$. In a series RLC circuit $Z = \sqrt{R^2 + (X_L - X_C)^2}$.
- The current leads or lags the voltage by ϕ with $\tan \phi = (X_L - X_C)/R$. Average power is $P = I_{\text{rms}} V_{\text{rms}} \cos \phi$; $\cos \phi$ is the power factor.
- At resonance $\omega_0 = 1/\sqrt{LC}$, $X_L = X_C$ and the current is largest.
- An ideal transformer keeps power: $V_2/V_1 = N_2/N_1$ and $I_2/I_1 = N_1/N_2$. It works only with AC, by mutual induction.
- Line loss is $I^2 R$. Sending the same power at 10 times the voltage cuts current 10 times and losses 100 times.

Key equations

$$V_{\text{rms}} = \frac{V_0}{\sqrt{2}}$$

RMS value

$$X_L = \omega L, \quad X_C = \frac{1}{\omega C}$$

Reactance

$$Z = \sqrt{R^2 + (X_L - X_C)^2}, \quad \tan \phi = \frac{X_L - X_C}{R}$$

Impedance and phase

$$P = I_{\text{rms}} V_{\text{rms}} \cos \varphi$$

Average power

$$\frac{V_2}{V_1} = \frac{N_2}{N_1}$$

Transformer

$$P_{\text{loss}} = I^2 R = \left(\frac{P}{V} \right)^2 R$$

Line loss

Worked examples, step by step

Example 9.1 A series circuit has $R = 20 \, \Omega$, $L = 0.1 \, \text{H}$ and $C = 100 \, \mu\text{F}$ on $120 \, \text{V RMS}$ at $60 \, \text{Hz}$. Find the impedance, current, phase and power.

1. $X_L = 2\pi \times 60 \times 0.1 = 37.7 \, \Omega$; $X_C = 1/(2\pi \times 60 \times 10^{-4}) = 26.5 \, \Omega$.
2. $Z = \sqrt{(20^2 + 11.2^2)} = 22.9 \, \Omega$; $I = 120/22.9 = 5.24 \, \text{A}$.
3. $\tan \varphi = 11.2/20$, $\varphi = 29.2^\circ$; $P = I^2 R = 549 \, \text{W}$.

Answer: $22.9 \, \Omega$, $5.24 \, \text{A}$, current lags by 29.2° (power factor 0.873), $549 \, \text{W}$.

Example 9.2 Send $100 \, \text{MW}$ over a line with $10 \, \Omega$ resistance at $345 \, \text{kV}$ and at $34.5 \, \text{kV}$. Compare the losses.

1. $345 \, \text{kV}$: $I = 290 \, \text{A}$, loss = $I^2 R = 0.84 \, \text{MW}$ (0.84%).
2. $34.5 \, \text{kV}$: $I = 2,899 \, \text{A}$, loss = $84 \, \text{MW}$.

Answer: $0.84 \, \text{MW}$ versus $84 \, \text{MW}$. Ten times the voltage gives one hundredth of the loss, which is why long lines run at hundreds of kilovolts.

Example 9.3 A pole transformer steps $7,200 \, \text{V}$ down to $240 \, \text{V}$ (sample values). Find the turns ratio, and the primary current when the secondary supplies $30 \, \text{A}$.

1. $N_1/N_2 = 7,200/240 = 30$.
2. $I_1 = I_2/30$.

Answer: 30:1; 1.0 A.

Practice problems

Work each on paper first, then check.

1. Find the peak voltage of 120 V RMS.

169.7 V.

2. Find the resonant frequency of the RLC circuit above.

$$f_0 = 1/(2\pi\sqrt{LC}) \approx 50.3 \text{ Hz.}$$

3. Why can't a transformer step up DC?

A steady current makes a steady flux, which induces no EMF.

4. What happens to X_C as frequency rises?

It falls: capacitors pass high frequencies.

Common misconceptions

Myth: RMS is the average voltage.

Actually: The average of a sine wave is zero; RMS is the root of the mean square.

Myth: A transformer makes power.

Actually: It trades voltage for current; power out $\leq$ power in.

Myth: Impedances add like resistances.

Actually: They add as vectors (phasors), not as plain numbers.

Flashcards

RMS

$$V_{\text{rms}} = V_0/\sqrt{2}.$$

Inductive reactance

$$X_L = \omega L.$$

Capacitive reactance

$$X_C = 1/(\omega C).$$

Impedance

$$Z = \sqrt{R^2 + (X_L - X_C)^2}.$$

Power factor

$$\cos \phi = R/Z.$$

Transformer

$$V_2/V_1 = N_2/N_1.$$

Line loss

$$I^2 R = (P/V)^2 R.$$

Self-check quiz

1. At resonance in a series RLC circuit...

$$X_L = X_C$$

$$Z = 0$$

$$I = 0$$

$$R = 0$$

$$X_L = X_C. \text{ Reactances cancel, } Z = R.$$

2. Raising transmission voltage 10 times changes line loss by...

$$\times 10$$

$$\times 1/10$$

$$\times 1/100$$

$$\times 100$$

$$\times 1/100. \text{ Loss} \propto I^2 \propto 1/V^2.$$

3. A step-up transformer has...

$$N_2 > N_1$$

$$N_2 < N_1$$

$$N_2 = N_1$$

no secondary

$$N_2 > N_1, V_2/V_1 = N_2/N_1.$$

4. A power factor of 1 means...

current and voltage in phase

no current

pure inductor

pure capacitor

current and voltage in phase. $\cos 0 = 1$.

Try this quiz again

How this helps save the planet

The U.S. Energy Information Administration estimates that transmission and distribution losses averaged about 5% of the electricity sent through the U.S. grid in 2018 through 2022. EIA describes the grid as thousands of miles of high-voltage power lines and millions of miles of low-voltage lines. High voltage for distance, then transformers down to safe levels near customers, is the worked example above at national scale. Every percent saved means less fuel burned or more clean power delivered.

On Saving Planets: [Physics I](#)

Sources: [U.S. EIA: How much electricity is lost in transmission and distribution?](https://www.eia.gov/tools/faqs/faq.php?id=105&t=3) (<https://www.eia.gov/tools/faqs/faq.php?id=105&t=3>) · [U.S. EIA: Delivery to consumers \(the power grid\)](https://www.eia.gov/energyexplained/electricity/delivery-to-consumers.php) (<https://www.eia.gov/energyexplained/electricity/delivery-to-consumers.php>)

Free learning resources

- [OpenStax UP2, 15.2 Simple AC circuits](https://openstax.org/books/university-physics-volume-2/pages/15-2-simple-ac-circuits) (<https://openstax.org/books/university-physics-volume-2/pages/15-2-simple-ac-circuits>): AC basics.
- [OpenStax UP2, 15.3 RLC series circuits with AC](https://openstax.org/books/university-physics-volume-2/pages/15-3-rlc-series-circuits-with-ac) (<https://openstax.org/books/university-physics-volume-2/pages/15-3-rlc-series-circuits-with-ac>): Impedance.
- [OpenStax UP2, 15.4 Power in an AC circuit](https://openstax.org/books/university-physics-volume-2/pages/15-4-power-in-an-ac-circuit) (<https://openstax.org/books/university-physics-volume-2/pages/15-4-power-in-an-ac-circuit>): Power factor.
- [OpenStax UP2, 15.6 Transformers](https://openstax.org/books/university-physics-volume-2/pages/15-6-transformers) (<https://openstax.org/books/university-physics-volume-2/pages/15-6-transformers>): Transformers.

- PhET: Circuit Construction Kit: AC (<https://phet.colorado.edu/en/simulations/circuit-construction-kit-ac>):
Interactive.



I finished this unit

Maxwell's Equations, Electromagnetic Waves and Optics

The displacement current and Maxwell's four equations, light as an electromagnetic wave, energy and momentum of light, the spectrum, and an introduction to optics: reflection, refraction, total internal reflection, polarization and thin lenses.

Learning objectives

By the end of this unit you can:

- State Maxwell's equations and the role of displacement current.
- Derive $c = 1/\sqrt{\mu_0\epsilon_0}$ and relate f , λ and photon energy.
- Compute intensity, field amplitudes and radiation pressure.
- Use Snell's law, the critical angle, Malus's law and the thin-lens equation.

Key concepts

- Maxwell added the displacement current $\epsilon_0 d\Phi_E/dt$ to Ampère's law. With it, the four equations (Gauss for E and B, Faraday, Ampère–Maxwell) predict waves.
- The waves travel at $c = 1/\sqrt{\mu_0\epsilon_0} = 3.00 \times 10^8$ m/s, with $E \perp B \perp$ direction of travel and $E = cB$. Light is one of these waves.
- Waves carry energy: intensity $I = \frac{1}{2}c\epsilon_0 E_0^2$, and momentum, pressure I/c on an absorber.
- The spectrum runs from radio through microwave, infrared, visible, ultraviolet and X-ray to gamma; $c = f\lambda$ and photon energy $E = hf$.
- At a boundary, light reflects at equal angles and refracts by Snell's law $n_1 \sin \theta_1 = n_2 \sin \theta_2$. Going from a denser medium, beyond the critical angle all light reflects.
- A polarizer passes $I = I_0 \cos^2 \theta$ (Malus). A thin lens obeys $1/f = 1/d_o + 1/d_i$.

Key equations

$$\oint \mathbf{E} \cdot d\mathbf{A} = \frac{Q}{\epsilon_0}, \quad \oint \mathbf{B} \cdot d\mathbf{A} = 0$$

Gauss's laws

$$\oint \mathbf{E} \cdot d\mathbf{l} = -\frac{d\Phi_B}{dt}, \quad \oint \mathbf{B} \cdot d\mathbf{l} = \mu_0 I + \mu_0 \epsilon_0 \frac{d\Phi_E}{dt}$$

Faraday and Ampère–Maxwell

$$c = \frac{1}{\sqrt{\mu_0 \epsilon_0}} = f\lambda, \quad E = cB$$

$$I = \frac{1}{2} c \epsilon_0 E_0^2, \quad p = \frac{I}{c}$$

Intensity and radiation pressure

$$n_1 \sin \theta_1 = n_2 \sin \theta_2$$

Snell's law

$$I = I_0 \cos^2 \theta, \quad \frac{1}{f} = \frac{1}{d_o} + \frac{1}{d_i}$$

Malus and thin lens

Worked examples, step by step

Example 10.1 Compute c from μ_0 and ϵ_0 .

$$1. \ c = 1/\sqrt{(4\pi \times 10^{-7} \times 8.854 \times 10^{-12})}.$$

Answer: 2.998×10^8 m/s, the measured speed of light, which told Maxwell that light is electromagnetic.

Example 10.2 Landsat 9's near-infrared band runs 0.85–0.88 μm and its red band 0.64–0.67 μm (NASA). Find the frequency at each band's center (0.865 and 0.655 μm) and the photon energy in the red.

$$1. \ f = c/\lambda: 3.47 \times 10^{14} \text{ Hz and } 4.58 \times 10^{14} \text{ Hz.}$$

$$2. \ E = hc/\lambda = 3.03 \times 10^{-19} \text{ J} = 1.89 \text{ eV.}$$

Answer: NIR 3.47×10^{14} Hz; red 4.58×10^{14} Hz; 1.89 eV.

Example 10.3 Bright sunlight of $1,000 \text{ W/m}^2$ (sample value) hits a panel. Find E_0 , B_0 and the pressure on an absorbing surface.

$$1. \ E_0 = \sqrt{(2I/(c\epsilon_0))} = 868 \text{ V/m.}$$

$$2. \ B_0 = E_0/c = 2.90 \text{ } \mu\text{T.}$$

$$3. \ p = I/c = 3.34 \text{ } \mu\text{Pa.}$$

Answer: 868 V/m, 2.90 μ T, 3.34 μ Pa.

Example 10.4 Light enters water ($n = 1.33$) at 30° from the normal. Find the refraction angle and the critical angle for light leaving water.

1. $\sin \theta_2 = \sin 30^\circ / 1.33$, $\theta_2 = 22.1^\circ$.

2. $\sin \theta_c = 1 / 1.33$, $\theta_c = 48.8^\circ$.

Answer: 22.1° ; 48.8° .

Practice problems

Work each on paper first, then check.

1. Find the wavelength of 2.4 GHz Wi-Fi.

12.5 cm.

2. About how long does sunlight take to cover 1.5×10^{11} m?

≈ 8.3 minutes.

3. Find the critical angle for glass ($n = 1.5$) to air.

41.8° .

4. Unpolarized light passes two polarizers at 60° . What fraction of the light leaving the first passes the second?

$\cos^2 60^\circ = 0.25$.

5. An object sits 30 cm from a lens of focal length 10 cm. Where is the image?

$1/d_i = 1/10 - 1/30$, $d_i = 15$ cm, real and inverted.

6. Landsat 9's thermal band 10 is near $11 \mu\text{m}$. Find the photon energy.

≈ 0.113 eV, far less than visible photons: thermal sensors read heat, not color.

Common misconceptions

Myth: Light needs a medium.

Actually: EM waves travel through vacuum.

Myth: Radio and light are different things.

Actually: Same waves, different wavelengths.

Myth: Light bends away from the normal entering water.

Actually: Toward the normal: it slows down.

Flashcards

Maxwell's equations

Gauss (E, B), Faraday, Ampère–Maxwell.

Displacement current

$\epsilon_0 d\Phi_E/dt$.

Speed of light

$c = 1/\sqrt{(\mu_0\epsilon_0)}$.

Wave relation

$c = f\lambda$.

Photon energy

$E = hf$.

Snell's law

$n_1 \sin \theta_1 = n_2 \sin \theta_2$.

Critical angle

$\sin \theta_c = n_2/n_1$.

Malus's law

$I = I_0 \cos^2\theta$.

Thin lens

$1/f = 1/d_o + 1/d_i$.

Self-check quiz

1. The displacement current term was added by...

Faraday

Ampère

Maxwell

Gauss

Maxwell. Ampère–Maxwell law.

2. In an EM wave, E and B are...

parallel

perpendicular to each other and to the motion

along the motion

unrelated

perpendicular to each other and to the motion. Transverse waves.

3. Higher frequency means...

longer λ , less energy per photon

shorter λ , more energy per photon

slower waves

no change

shorter λ , more energy per photon. $c = f\lambda$; $E = hf$.

4. Total internal reflection happens when light goes from...

air into water

water into air beyond θ_c

any medium

vacuum into glass

water into air beyond θ_c . Denser to less dense.

Try this quiz again

How this helps save the planet

Satellites watch the planet by measuring electromagnetic waves. NASA lists Landsat 9's bands, from the coastal/aerosol band at 0.43 μm through visible, near-infrared and shortwave infrared to thermal infrared at 10.60–12.51 μm . NASA says these observations support tropical deforestation alerts, water-quality monitoring and crop condition reports, and the thermal sensor measures land surface temperature to help manage water in drought-prone regions. Each band is a slice of the spectrum chosen because land, water and plants reflect or emit it differently.

NASA's tour of the electromagnetic spectrum shows how each band, from radio to gamma rays, is used to study Earth and space.

On Saving Planets: [Landsat 9](#) · [GOES-19](#) · [Earth Observation](#)

Sources: [NASA Landsat Science: Landsat 9 instruments and spectral bands \(https://landsat.gsfc.nasa.gov/satellites/landsat-9/landsat-9-instruments/\)](#) · [NASA Science: Tour of the electromagnetic spectrum \(https://science.nasa.gov/ems/\)](#)

Free learning resources

- [OpenStax UP2, 16.1 Maxwell's equations and electromagnetic waves \(https://openstax.org/books/university-physics-volume-2/pages/16-1-maxwells-equations-and-electromagnetic-waves\)](https://openstax.org/books/university-physics-volume-2/pages/16-1-maxwells-equations-and-electromagnetic-waves): Maxwell.
- [OpenStax UP2, 16.3 Energy carried by EM waves \(https://openstax.org/books/university-physics-volume-2/pages/16-3-energy-carried-by-electromagnetic-waves\)](https://openstax.org/books/university-physics-volume-2/pages/16-3-energy-carried-by-electromagnetic-waves): Intensity.
- [OpenStax UP2, 16.5 The electromagnetic spectrum \(https://openstax.org/books/university-physics-volume-2/pages/16-5-the-electromagnetic-spectrum\)](https://openstax.org/books/university-physics-volume-2/pages/16-5-the-electromagnetic-spectrum): Spectrum.
- [OpenStax UP3, 1.3 Refraction \(https://openstax.org/books/university-physics-volume-3/pages/1-3-refraction\)](https://openstax.org/books/university-physics-volume-3/pages/1-3-refraction): Snell's law.
- [OpenStax UP3, 1.7 Polarization \(https://openstax.org/books/university-physics-volume-3/pages/1-7-polarization\)](https://openstax.org/books/university-physics-volume-3/pages/1-7-polarization): Polarization.
- [OpenStax UP3, 2.4 Thin lenses \(https://openstax.org/books/university-physics-volume-3/pages/2-4-thin-lenses\)](https://openstax.org/books/university-physics-volume-3/pages/2-4-thin-lenses): Lenses.
- [PhET: Bending Light \(https://phet.colorado.edu/en/simulations/bending-light\)](https://phet.colorado.edu/en/simulations/bending-light): Interactive.



I finished this unit

The lab (PHYS 210L)

The lab is the hands-on part of the course, a 1-credit component in a typical college schedule. Here it is free and for practice only.

Every lab can be done fully in a free PhET simulation, and most also have a home version that uses only batteries of 9 V or less. Never use wall power, never open a device that plugs into the wall, and never short a battery.

Safety reference: [OSHA: Electrical safety \(https://www.osha.gov/electrical\)](https://www.osha.gov/electrical)

Lab A: Mapping electric fields and equipotentials

WEEK 2

Goal: Measure how the field of a point charge falls with distance, confirm the inverse-square law with a log-log fit, and map equipotentials around a dipole.

$$E = \frac{kq}{r^2} \Rightarrow \log E = \log(kq) - 2 \log r$$

A straight line of slope -2 on a log-log plot

Procedure

1. Open PhET Charges and Fields. Place a single +1 nC charge and turn on the values and grid.
2. Use the E-field sensor at 0.5, 1.0, 1.5 and 2.0 m and record E.
3. Plot log E against log r and fit a line; compare the slope with -2 and the intercept with log(kq).
4. Add a -1 nC charge 1 m away, use the voltmeter tool to trace the 0 V and ± 10 V equipotentials, and sketch field lines perpendicular to them.

Data table

r (m)	E (V/m)
0.5	35.95
1.0	8.99
1.5	3.99
2.0	2.25

Values computed from $E = kq/r^2$ for $q = 1$ nC; your simulation readings should match to within rounding.

Sample calculation

1. From 0.5 m to 2.0 m ($\times 4$ in r), E falls from 35.95 to 2.25 V/m ($\times 1/16$), so the log-log slope is -2.
2. The 0 V equipotential of the dipole is the perpendicular bisector of the two charges, yet the field there is not zero.

Safety

- None beyond normal computer use.

Home or virtual alternative

- Rub a balloon on hair and watch it lift paper bits at different distances: a qualitative look at a field that falls off quickly with distance.

PhET: Charges and Fields (<https://phet.colorado.edu/en/simulations/charges-and-fields>) · PhET: Coulomb's Law (<https://phet.colorado.edu/en/simulations/coulombs-law>)

Planet link: Field maps like these are how engineers design the electric fields inside solar cells and high-voltage equipment. [U.S. DOE: How does solar work?](https://www.energy.gov/eere/solar/how-does-solar-work) (<https://www.energy.gov/eere/solar/how-does-solar-work>).



I completed this lab (wet or virtual)

Lab B: Capacitance and plate separation

WEEK 5

Goal: Measure how a parallel-plate capacitor's capacitance depends on plate separation, and extract ϵ_0 from the data.

$$C = \frac{\epsilon_0 A}{d}$$

Plot C against $1/d$; the slope is $\epsilon_0 A$

Procedure

1. Open PhET Capacitor Lab: Basics. Set the plate area to 400 mm^2 and connect the battery at 1.5 V .
2. Read C at plate separations of 2, 4, 6, 8 and 10 mm.
3. Plot C against $1/d$ and fit a line through the origin; divide the slope by A to get ϵ_0 .
4. At $d = 5 \text{ mm}$, record the stored energy and compare with $\frac{1}{2}CV^2$.

Data table

d (mm)	C (pF)
2	1.77
4	0.885
6	0.590
8	0.443
10	0.354

Values computed from $C = \epsilon_0 A/d$; simulation readouts round them.

Sample calculation

1. $C \times d$ is constant: $1.77 \text{ pF} \times 2 \text{ mm} = 0.354 \text{ pF} \times 10 \text{ mm}$, so $C \propto 1/d$.
2. Slope $\epsilon_0 A = 3.54 \times 10^{-15} \text{ F}\cdot\text{m}$, so $\epsilon_0 = 3.54 \times 10^{-15}/(4 \times 10^{-4}) = 8.85 \times 10^{-12} \text{ F/m}$.
3. At 5 mm, $C = 0.708 \text{ pF}$ and $U = \frac{1}{2}CV^2 = 0.797 \text{ pJ}$ at 1.5 V .

Safety

- None beyond normal computer use.

Home or virtual alternative

- Optional: with a multimeter that reads capacitance, measure two pieces of aluminum foil separated by one, two and three sheets of paper. C should fall as the stack grows.

PhET: Capacitor Lab: Basics (<https://phet.colorado.edu/en/simulations/capacitor-lab-basics>)

Planet link: Capacitors smooth power in electric cars, solar inverters and the grid; the same $C = \kappa\epsilon_0 A/d$ sets their size. [FuelEconomy.gov \(DOE/EPA\): All-electric vehicles \(https://www.fueleconomy.gov/feg/evtech.shtml\)](https://www.fueleconomy.gov/feg/evtech.shtml)



I completed this lab (wet or virtual)

Lab C: Ohm's law, Kirchhoff's rules and an RC time constant

WEEK 7

Goal: Confirm Ohm's law, check Kirchhoff's rules in a two-loop circuit, and measure the time constant of a charging capacitor.

$$V_C = V_0 \left(1 - e^{-t/RC}\right)$$

Charging curve; $\ln(1 - V_C/V_0) = -t/RC$ is a straight line

Procedure

1. Ohm's law: put a 1 k Ω resistor across 1.5, 3.0, 4.5, 6.0 and 9.0 V (AA cells in series, or the PhET battery) and record the current; plot I against V.
2. Kirchhoff: in PhET Circuit Construction Kit: DC, build the Unit 4 circuit (12 V, 6 V, 2 Ω , 3 Ω , 6 Ω) and measure the three currents; check the junction and loop sums.
3. RC: charge a 100 μ F capacitor from 9 V through 10 k Ω , reading V_C every second; plot $\ln(1 - V_C/9)$ against t and find RC from the slope.

Data table

t (s)	V_C (V), 10 k Ω and 100 μ F from 9 V
0	0.00
1	5.69
2	7.78
3	8.55
5	8.94

Values computed for ideal parts; real capacitors are often $\pm 20\%$ from their label, so your τ may differ.

Sample calculation

1. Ohm's law: the slope of I against V is 1 mA/V, so $R = 1.00$ k Ω ; at 9 V the resistor dissipates only 81 mW.
2. Kirchhoff: 2 A – 0.667 A = 1.33 A at the junction, and $12 - 2(2) - 6(1.33) = 0$ around loop 1.
3. RC: the line through $\ln(1 - V_C/9)$ has slope -1.0 s $^{-1}$, so $\tau = 1.0$ s = (10 k Ω)(100 μ F).

Safety

- Use only batteries of 9 V or less; never wall power.
- Never connect a wire straight across a battery: it heats fast and can burn.

- Electrolytic capacitors have a + lead; connect it toward the battery's + side, and use one rated above 9 V.

Home or virtual alternative

- Everything here works with a multimeter, AA cells, a 9 V battery, resistors and a capacitor on a breadboard; time the RC readings with a phone video of the meter.

PhET: Circuit Construction Kit: DC (<https://phet.colorado.edu/en/simulations/circuit-construction-kit-dc>) · PhET: Ohm's Law (<https://phet.colorado.edu/en/simulations/ohms-law>) · PhET: Resistance in a Wire (<https://phet.colorado.edu/en/simulations/resistance-in-a-wire>)

Planet link: Solar arrays are wired by the same rules: series strings raise voltage and parallel strings raise current. U.S. DOE: How does solar work? (<https://www.energy.gov/eere/solar/how-does-solar-work>)



I completed this lab (wet or virtual)

Lab D: Measuring magnetic fields, including Earth's

WEEK 9

Goal: Measure Earth's magnetic field with a phone magnetometer, map the field of a wire in simulation, and compare both with theory.

$$B = \frac{\mu_0 I}{2\pi r}$$

Field of a long wire

Procedure

1. Open a magnetometer app away from metal and electronics. Record the total field magnitude at five spots and average them.
2. Compare with NOAA's stated range of about 25,000–65,000 nT at Earth's surface.
3. In PhET Magnets and Electromagnets, see how the field changes with current and number of loops; then compute B for a long wire with $I = 2$ A at $r = 1, 2$ and 4 cm and plot B against $1/r$.
4. Bring a fridge magnet toward the phone and note the distance at which its field equals Earth's.

Data table

r (cm)	B for a 2 A wire (μ T)
1	40
2	20
4	10

Wire values computed from $\mu_0 I / (2\pi r)$. Earth-field readings depend on your location; NOAA's calculator gives the expected total for your spot.

Sample calculation

1. $B \propto 1/r$: doubling the distance halves the field, so the plot of B against $1/r$ is a straight line through the origin with slope $\mu_0 I / (2\pi) = 0.4 \mu\text{T}\cdot\text{m}$.
2. A 2 A wire matches Earth's 50 μT field at $r = \mu_0 I / (2\pi \times 50 \mu\text{T}) = 0.8$ cm.

Safety

- Keep strong magnets away from phones' card slots, pacemakers and credit cards.
- Do not run high current through bare wire at home; the wire part of this lab is done in simulation.

Home or virtual alternative

- The magnetometer and fridge-magnet steps are the home version.

PhET: Magnets and Electromagnets (<https://phet.colorado.edu/en/simulations/magnets-and-electromagnets>) ·

PhET: Magnet and Compass (<https://phet.colorado.edu/en/simulations/magnet-and-compass>) · NOAA magnetic field calculators (<https://www.ngdc.noaa.gov/geomag/calculators/magcalc.shtml>)

Planet link: Knowing the normal field is the baseline for spotting geomagnetic storms, which NOAA warns can induce harmful currents in power grids. NOAA NCEI: Geomagnetism frequently asked questions (<https://www.ngdc.noaa.gov/geomag/faggeom.shtml>) · NOAA Space Weather Prediction Center: Geomagnetic storms (<https://www.swpc.noaa.gov/phenomena/geomagnetic-storms>)



I completed this lab (wet or virtual)

Lab E: Induction and a model generator

WEEK 10

Goal: Show that induced EMF depends on the rate of change of flux, and that a generator's peak EMF grows in proportion to its spin rate.

$$\varepsilon_{\max} = NBA\omega$$

Peak EMF of a spinning coil

Procedure

1. In PhET Faraday's Law, push the magnet through the coil slowly and then quickly; record the peak voltage reading each time and note the sign change when it leaves.
2. In PhET Faraday's Electromagnetic Lab (Generator tab), change the turbine speed and record the peak bulb or voltmeter response.
3. Compute $\varepsilon_{\max}$ for a model coil with $N = 200$, $A = 0.01 \text{ m}^2$ and $B = 0.05 \text{ T}$ at 1, 2 and 3 revolutions per second.
4. Home: wind 100 turns of thin insulated wire around a toilet-paper tube, connect a multimeter on mV, and drop a strong magnet through it.

Data table

Spin rate (rev/s)	Peak EMF (V)
1	0.628
2	1.26
3	1.88

Values computed for the model coil (sample values).

Sample calculation

1. $\varepsilon_{\max} = NBA(2\pi f) = 200 \times 0.05 \times 0.01 \times 2\pi f = 0.628 \text{ V per rev/s}$, so doubling the speed doubles the EMF.
2. A faster magnet gives a taller, shorter pulse; the area under the EMF-time curve (total flux change $\times N$) stays the same.

Safety

- Strong neodymium magnets snap together hard and can pinch skin or shatter; handle one at a time.
- Keep magnets away from pacemakers and electronics.

Home or virtual alternative

- The coil-and-magnet step is the home version; any multimeter on its millivolt range works.

PhET: Faraday's Law (<https://phet.colorado.edu/en/simulations/faradays-law>) · PhET: Faraday's Electromagnetic Lab (<https://phet.colorado.edu/en/simulations/faradays-electromagnetic-lab>) · PhET: Generator (<https://phet.colorado.edu/en/simulations/generator>)

Planet link: Every wind turbine and hydro plant runs this lab at megawatt scale: the turbine spins a generator to make electricity. U.S. DOE: How do wind turbines work? (<https://www.energy.gov/eere/wind/how-do-wind-turbines-work>) · U.S. DOE: How hydropower works (<https://www.energy.gov/eere/water/how-hydropower-works>)



I completed this lab (wet or virtual)

Lab F: Refraction and Snell's law

WEEK 14

Goal: Measure refraction angles from air into water, find the index of refraction, and observe total internal reflection.

$$n = \frac{\sin \theta_1}{\sin \theta_2}$$

Slope of $\sin \theta_1$ against $\sin \theta_2$

Procedure

1. In PhET Bending Light, set the lower medium to water and shine the laser at 10° to 60° from the normal in 10° steps; read the refraction angle with the protractor tool.
2. Plot $\sin \theta_1$ against $\sin \theta_2$ and fit a line through the origin; the slope is n .
3. Put the laser in the water and increase the angle until the refracted beam vanishes; record the critical angle.
4. Home: shine a low-power laser or narrow flashlight beam into a clear box of water with a drop of milk and measure the angles on a printed protractor.

Data table

θ_1 in air ($^\circ$)	θ_2 in water ($^\circ$)
10	7.5
20	14.9
30	22.1
40	28.9
50	35.2
60	40.6

Values computed from Snell's law with $n = 1.33$.

Sample calculation

1. $\sin 30^\circ / \sin 22.1^\circ = 0.500 / 0.376 = 1.33$, and every row gives the same ratio.
2. Critical angle from water to air: $\sin^{-1}(1/1.33) = 48.8^\circ$.

Safety

- Use only a class 2 (under 1 mW) laser pointer, and never look into the beam or aim it at anyone's eyes; watch for reflections off the water and glass.

Home or virtual alternative

- The water-box step is the home version.

PhET: Bending Light (<https://phet.colorado.edu/en/simulations/bending-light>)

Planet link: Satellite sensors are built from lenses, mirrors and filters designed with these same laws of refraction and reflection. NASA Landsat Science: Landsat 9 instruments and spectral bands (<https://landsat.gsfc.nasa.gov/satellites/landsat-9/landsat-9-instruments/>)



I completed this lab (wet or virtual)

Exam prep practice sets

Time yourself: about 10 minutes per problem. Then compare with the full solutions.

Midterm practice set (Units 1–5)

1. Charges of $+2.0 \mu\text{C}$ and $+8.0 \mu\text{C}$ are 0.30 m apart. Find the force between them and the point between them where $E = 0$.

1. $F = k(2 \times 10^{-6})(8 \times 10^{-6})/0.09$.

2. $k(2)/x^2 = k(8)/(0.3 - x)^2$ gives $x = 0.10 \text{ m}$.

Answer: 1.60 N , repulsive; 0.10 m from the $2.0 \mu\text{C}$ charge.

2. A closed surface surrounds a 3.0 nC charge. Find the net flux.

1. $\Phi = Q/\epsilon_0$.

Answer: $\approx 339 \text{ N}\cdot\text{m}^2/\text{C}$.

3. A $10 \mu\text{F}$ capacitor is charged to 12 V . Find Q and U .

1. $Q = CV$; $U = \frac{1}{2}CV^2$.

Answer: $120 \mu\text{C}$; 0.72 mJ .

4. A 9 V battery drives 3Ω in series with a parallel pair of 6Ω and 3Ω . Find the current and total power.

1. Parallel pair = 2Ω ; total 5Ω .

2. $I = 9/5$; $P = IV$.

Answer: 1.8 A; 16.2 W.

5. A proton moves at 1.0×10^6 m/s across a 0.20 T field. Find the orbit radius.

1. $r = mv/(eB)$.

Answer: ≈ 5.22 cm.

Final practice set (all units)

1. Find B 0.10 m from a long wire carrying 50 A.

1. $B = \mu_0 I / (2\pi r)$.

Answer: 100 μ T, about twice Earth's field.

2. A 50-turn coil of area 0.05 m² spins at 50 rev/s in a 0.20 T field. Find the peak EMF.

1. $\varepsilon = NBA\omega$, $\omega = 2\pi \times 50$.

Answer: ≈ 157 V.

3. An RL circuit has $L = 0.5$ H and $R = 100 \Omega$. Find τ and the fraction of the final current after 5 ms.

1. $\tau = L/R$.

Answer: 5 ms; 63%.

4. Send 50 MW at 230 kV over a line with 5 Ω resistance. Find the current and loss.

1. $I = P/V$; $\text{loss} = I^2 R$.

Answer: 217 A; 0.236 MW (0.47%).

5. Find the frequency and photon energy of 500 nm light.

1. $f = c/\lambda$; $E = hf$.

Answer: 6.00×10^{14} Hz; 2.48 eV.

6. Light enters glass ($n = 1.5$) at 45° . Find the refraction angle.

1. $\sin \theta_2 = \sin 45^\circ / 1.5$.

Answer: 28.1° .

Formula sheet

$$F = k|q_1 q_2|/r^2$$

$$E = F/q$$

$$\oint \vec{E} \cdot d\vec{A} = Q_{\text{enc}}/\epsilon_0$$

$$V = kq/r, E_x = -dV/dx$$

$$C = \kappa\epsilon_0 A/d, U = \frac{1}{2}CV^2$$

$$V = IR, R = \rho L/A, P = IV$$

$$\tau = RC, \tau = L/R$$

$$\vec{F} = q\vec{v} \times \vec{B}, r = mv/(qB)$$

$$\vec{F} = I\vec{L} \times \vec{B}, \tau = NIAB \sin \theta$$

$$B = \mu_0 I/(2\pi r), B = \mu_0 nI$$

$$\mathcal{E} = -N d\Phi_B/dt, \mathcal{E} = BLv$$

$$L = \mu_0 N^2 A/l, U = \frac{1}{2}LI^2$$

$$X_L = \omega L, X_C = 1/(\omega C), Z = \sqrt{R^2 + (X_L - X_C)^2}$$

$$V_2/V_1 = N_2/N_1$$



$$c = 1/\sqrt{\mu_0\epsilon_0} = f\lambda, E = hf$$

$$n_1 \sin \theta_1 = n_2 \sin \theta_2, 1/f = 1/d_o + 1/d_i$$

Constants

Constant	Value
Elementary charge, e	$1.602 \times 10^{-19} \text{ C}$
Coulomb constant, $k = 1/(4\pi\epsilon_0)$	$8.988 \times 10^9 \text{ N}\cdot\text{m}^2/\text{C}^2$
Vacuum permittivity, ϵ_0	$8.854 \times 10^{-12} \text{ F/m}$
Vacuum permeability, μ_0	$1.257 \times 10^{-6} \text{ T}\cdot\text{m/A}$ ($\approx 4\pi \times 10^{-7}$)
Speed of light, c	$2.998 \times 10^8 \text{ m/s}$
Electron mass, m_e	$9.109 \times 10^{-31} \text{ kg}$
Proton mass, m_p	$1.673 \times 10^{-27} \text{ kg}$
Planck constant, h	$6.626 \times 10^{-34} \text{ J}\cdot\text{s}$

Source: [NIST: Fundamental physical constants \(https://physics.nist.gov/cuu/Constants/\)](https://physics.nist.gov/cuu/Constants/)

Free texts and simulations

Use these free textbooks, lectures and simulations alongside the course.

- [OpenStax University Physics Volume 2](https://openstax.org/books/university-physics-volume-2/pages/1-introduction) (<https://openstax.org/books/university-physics-volume-2/pages/1-introduction>): Free, complete textbook for this course.
- [MIT OpenCourseWare 8.02 Physics II: Electricity and Magnetism](https://ocw.mit.edu/courses/8-02-physics-ii-electricity-and-magnetism-spring-2019/) (<https://ocw.mit.edu/courses/8-02-physics-ii-electricity-and-magnetism-spring-2019/>): Free MIT lectures, problem sets and exams.
- [OpenStax University Physics Volume 3 \(optics\)](https://openstax.org/books/university-physics-volume-3/pages/1-2-the-law-of-reflection) (<https://openstax.org/books/university-physics-volume-3/pages/1-2-the-law-of-reflection>): Free optics chapters for Unit 10.
- [PhET: Charges and Fields](https://phet.colorado.edu/en/simulations/charges-and-fields) (<https://phet.colorado.edu/en/simulations/charges-and-fields>): Place charges and map fields and equipotentials.
- [PhET: Circuit Construction Kit: DC](https://phet.colorado.edu/en/simulations/circuit-construction-kit-dc) (<https://phet.colorado.edu/en/simulations/circuit-construction-kit-dc>): Build and measure circuits.
- [PhET: Faraday's Electromagnetic Lab](https://phet.colorado.edu/en/simulations/faradays-electromagnetic-lab) (<https://phet.colorado.edu/en/simulations/faradays-electromagnetic-lab>): Magnets, coils, generators and transformers.

Glossary

Ampère's law

$$\oint \mathbf{B} \cdot d\mathbf{l} = \mu_0 I_{\text{enc.}}$$

Capacitance

Charge stored per volt, $C = Q/V$.

Coulomb's law

Force between point charges, $F = k|q_1 q_2|/r^2$.

Critical angle

Angle beyond which light is totally reflected inside a denser medium.

Displacement current

$\epsilon_0 d\Phi_E/dt$, Maxwell's addition to Ampère's law.

EMF

Energy per charge supplied by a source such as a battery or generator.

Electric field

Force per unit charge.

Electric potential

Potential energy per unit charge, in volts.

Faraday's law

Changing magnetic flux induces EMF.

Gauss's law

Net electric flux out of a closed surface equals $Q_{\text{enc}}/\epsilon_0$.

Geomagnetically induced current

Current driven in grids and pipelines by geomagnetic storms.

Impedance

Total opposition to AC, Z .

Inductance

EMF per rate of change of current, in henries.

Lenz's law

Induced current opposes the change in flux.

Magnetic flux

$\Phi_B = \int \mathbf{B} \cdot d\mathbf{A}$, in webers.

Maxwell's equations

Four laws that unify electricity, magnetism and light.

Power factor

$\cos \phi$, the fraction of apparent power that does work.

RMS value

Root-mean-square, $V_0/\sqrt{2}$ for a sine wave.

Resistivity

Material property ρ in $R = \rho L/A$.

Snell's law

$n_1 \sin \theta_1 = n_2 \sin \theta_2$.

Transformer

Two coupled coils that change AC voltage.

Self-assessment rubric

No grade or credit is given. Use this to judge honestly where you are in each unit.

Level	What it looks like
4 · Mastery	Sets up fields and circuits from a description, chooses the right law, handles signs and directions, and checks units and limits.
3 · Proficient	Solves the practice problems with occasional sign or unit slips.
2 · Developing	Follows worked examples but struggles to choose a Gaussian surface, loop or right-hand rule.
1 · Beginning	Plugs numbers into formulas without a picture; needs to revisit the unit.

Suggested weighting if you want a score

Part	Weight
Practice problems	25%
Labs (PHYS 210L)	20%
Midterm practice set	25%

Part	Weight
Final practice set	30%

Aim for level 3 or better in every unit before moving to the next course.